

AWG (American Wire Gauge) to mm² (Millimetres squared) Conversion

AWG to mm ² Conversion Table	
AWG/Kcmil	mm ² *
20	0.52
18	0.82
16	1.31
14	2.08
12	3.31
10	5.26
8	8.36
6	13.3
4	21.2
2	33.6
1	42.4
1/0	53.5
2/0	67.4
3/0	85.0
4/0	107
250	127
300	152
350	177
400	203
450	228
500	253
600	304
750	380
800	405
1000	507

* Equivalent mm² cross-sectional area

mm ² to AWG Conversion Table		
mm ²	mm ² *	AWG/Kcmil
0.5	0.52	20
0.75	0.82	18
1.5	1.31	16
2.5	2.08	14
2.5	3.31	12
4	3.31	12
6	5.26	10
10	8.36	8
16	13.3	6
25	21.2	4
35	33.6	2
35	42.4	1
50	53.5	1/0
70	67.4	2/0
95	85.0	3/0
95	107	4/0
120	107	4/0
120	127	250
150	152	300
185	177	350
185	203	400
240	228	450
240	253	500
300	304	600
400	380	750
400	405	800
500	507	1000

Multiple AWG choices — consult responsible engineer for required ampacity

Get in touch for any technical questions regarding US spec cables
sales@thompsongws.com